



Switch	ON	OFF (delivery status)
1	Deadman operation activated.	Deadman button mode deactivated.
2	Reaction to SKL input/force cut-off	
	Full reversing	Partial reversing
3	Weight potentiometer blocked.	Weight potentiometer unblocked.
4	Reaction to light barrier when closing	
	Full reversing	Partial reversing
5	Power-saving mode	
	Power-saving mode deactivated	Power-saving mode activated
6	Gate closes 5 seconds after triggering light barrier.	Triggering light barrier resets the open holding time.
7	Gate right stop.	Gate left stop.
8	Early warning time activated.	Early warning time deactivated.

Terminal Mem:039 -> 1

Option:
8.2 K Ω safety edge 8.2 K Ω

Option:
8.2 K Ω safety edge 8.2 K Ω

If several 8.2 K Ω edges are wired in series, only one resistor can still be used

If several 8.2 K Ω edges are wired in series, only one resistor can still be used

Option: Optoelectronic SKL

Option: Optoelectronic SKL